

■ Commutative laws: $A + B = B + A$
 $AB = BA$

■ Associative laws: $A + (B + C) = (A + B) + C$
 $A(BC) = (AB)C$

■ Distributive law: $A(B + C) = AB + AC$

■ Boolean rules:

1. $A + 0 = A$	7. $A \cdot A = A$
2. $A + 1 = 1$	8. $A \cdot \bar{A} = 0$
3. $A \cdot 0 = 0$	9. $\overline{\bar{A}} = A$
4. $A \cdot 1 = A$	10. $A + AB = A$
5. $A + A = A$	11. $A + \bar{A}B = A + B$
6. $A + \bar{A} = 1$	12. $(A + B)(A + C) = A + BC$

■ DeMorgan's theorems:

1. The complement of a product is equal to the sum of the complements of the terms in the product.

$$\overline{XY} = \bar{X} + \bar{Y}$$

2. The complement of a sum is equal to the product of the complements of the terms in the sum.

$$\overline{X + Y} = \bar{X}\bar{Y}$$